

6 HOURS LASTING

EMERGENCY LED BULB

Features



- 1 1800ma rechargeable battery
- 2 years warranty
- 2 Switch to battery power backup in 1 second after power off
- 3 96-265V wide voltage input
- 4 Detect circuit automatically IC control emergency lighting



BAT led lamps is based on a LED lamp with a built in battery that is charged by grid when lamp is on.If grid disappears the lamp continue to be working for up to 6 hours.

Features and advantages

- * Starts when grid turs off so the perfect emergency lamp in critical areas
- * Integrated battery that is charged from grid when on
- * In areas with unreliable grid this see that it is light with no extra back up system

Picture	Size(mm)	Watt (W)	Voltage(V)	Holder	PF	Lumen	CR I	Color Temperature	Work time after off power
	69*122	7 W	AC85-265V	E27/B22	>0.5	450-500LM	≥70	6000-6500K 2700-3500K	2.5-3H
	80*130	9 W	AC85-265V	E27/B22	>0.5	650-700LM	≥70	6000-6500K 2700-3500K	2.5-3H
	95*150	12 W	AC85-265V	E27/B22	>0.5	850-900LM	≥70	6000-6500K 2700-3500K	2-3H
	59*108	5 W	AC85-265V	E27/B22	>0.5	350-400LM	≥70	6000-6500K 2700-3500K	6-7H
	69*122	7 W	AC85-265V	E27/B22	>0.5	450-500LM	≥70	6000-6500K 2700-3500K	4-5H
	80*130	9 W	AC85-265V	E27/B22	>0.5	650-700LM	≥70	6000-6500K 2700-3500K	3-4H
	95*150	12 W	AC85-265V	E27/B22	>0.5	850-900LM	≥70	6000-6500K 2700-3500K	2-3H
	95*150	15 W	AC85-265V	E27/B22	>0.5	950-1100LM	≥70	6000-6500K 2700-3500K	1.5-2H



Reasonable priced security led lamp that saves money when activated as it us high efficiency led emitters. When power is lost it become a security and emergency lamp so every one in area can see and move with no problems.

